

[System requirements] of Memory Media Utility Software Ver 4.7.0 for Windows (released at 19/Jul./2022) is revised.

This document describes how to install Memory Media Utility Software and its precautions.

Refer to the operation manual supplied with the SxS Reader/Writer such as SBAC-T40 and the Portable Storage such as PSZ-SC48/96.

#### [Additional Items in V4.7.0]

- Support for Updating the Ver.2.16 firmware of SBAC-US30/SBAC-UT100  
(Improved stability when connecting SxS Pro X memory)

#### [System requirements]

The Memory Media Utility Ver. 4.7.0 has been tested under the following conditions.

- Operating system
    - Windows 10 64bit [22H2](#)
    - Windows 11 64bit [24H2](#)
  - Memory
    - 4GB or more
  - Free hard disk space
    - 500MB or more
- Note: These test results may not apply to all computers.

#### 【Installing Memory Media Utility】

-Unzip [MemoryMediaUtility\_4\_7\_0\_win.zip].

Double-click MemoryMediaUtility\_4\_7\_0\_win.exe and follow the instructions of the installer.

The media management database registered in the previous version will be inherited, so select the old version in "Programs and Features", delete it, and then install it.

Please restart the OS after installation to ensure that the setting information is reflected.

#### [Language]

Memory Media Utility automatically switches between EN and JP according to the language that a system is operating in.

#### [Restrictions]

- Ejecting media:  
You can eject with the Eject button of each drive displayed on the "SxS Reader/Writer Display" screen.  
However, the SBAC-T40 must be removed from "Safely remove hardware" in Windows.

## [Precautions]

### 1. Operating Utility

- If you start operating Utility before the mount is completed, the computer may become unstable.
  - Make sure to complete mounting media on OS, and then start operating Utility.
  - If you mount it with the OS standard file system driver, access will be slow, so please mount the media after the OS starts.
- Fully formatting the SxS memory card, and updating the firmware of the SxS Reader/Writer.
  - Formatting cannot be performed when a media is accessed or opened by Finder and Application.
  - After updating the firmware, remove the SxS reader/writer, wait at least 5 seconds, and then reconnect.
  - If you disconnect the cable during operation, the media may be damaged or your computer may become unstable. If this happens, wait a moment and then reinsert the SxS memory or restart your computer. If the media or reader/writer is not broken, it will return to normal.

### 2. Setting a computer

It is recommended to use the computer in "High-performance mode." Other mode setting may interfere with the proper operation of SxS Reader/Writer drive.

Alternatively, use it with the automatic sleep disabled temporarily.

For Windows,

If you set the display method of the control panel to icons, open Power Options > Change plan settings > Change advanced power settings) in the control panel and change the following items (If you set the display method to category, the hierarchy will be deeper).

- [Sleep]-[Sleep after the next time] : "None"
- [USB]-[USB Setting]-[USB Selective Suspend Setting] : "Disable"

The Thunderbolt power saving mode can be changed in the UEFI BIOS before starting the OS. Please contact your PC manufacturer for proper BIOS settings for your PC.

For HP Elitebook, you can change it by setting Advanced > Port Options > Thunderbolt PCIe Hot plug Mode in UEFI BIOS to "Native + Lower Power mode" and confirming with Save and Exit in Main Menu.

The following storage management software may also be improved by temporarily disabling it or excluding it from the management target.

Ex) Resident anti-virus software, backup tool, self-encrypting drive management service, RAID management software

### 3. Initializing SxS Memory card and SONY Portable Storage or Professional RAID

Make sure to perform formatting media by the format function of Memory Media Utility. Do not initialize with the OS standard format function. Can be mounted with Sony camcorders and player/recorders.

### 4. To use Memory Media Utility or a UDF formatted memory card

If you want to use the Memory Media Utility or use the functions related to UDF-formatted SxS memory

cards, you need to install the SxS UDF Driver V2.6.0. Please download and install from Sony' s web site.

<https://pro.sony/product-resources/product-resources-search/>

\* You can select your region and language under [Change Country, Region or Language] at the bottom of the page. In addition, you can obtain this software and documentation by searching for the target model name, such as "SBAC-US30."

5. To use SxS reader/writer "SBAC-T40" or an ExpressCard slot:

Using SxS Memory Card to connect the SBAC-T40 or ExpressCard Slot of PC, you need to install the SxS Device Driver. Please obtain another product, SxS Device Driver V3.1.0 from the above URL and install it.

6. To use SxSPROX memory card

If the firmware of the SxS reader/writer is old, the connection with the PC may not be stable. In that case, it can be improved by updating to the latest firmware included in this software.

---