

SOFTWARE INFORMATION

BZE-9611/01 MIXER CONTROL PROGRAM V5.03 FOR BVE-9100

Product: **BVE-9100, BZE-9611/01**

Serial No: **All**

DESCRIPTION

BZE-9611/01 mixer control program V5.03 for the BVE-9100 has been released. This software supersedes V5.02.

IMPROVEMENT

On D/ESAM-820 and other mixers, audio mute can now be reset on selected channels when the PVW BUS is used for monitoring and one of the audio mute buttons (A1–A4) is set to mute in PVW or REC mode.

INSTALLATION PROCEDURE

1. Boot the BVE-9100 using the System Disks.
2. Insert the BZE-9611/01 disk into drive A.
3. Insert the System Disk that contains the MXDLG(2).OBJ and MIXER(2).IDC files into drive B.
4. Press the CTRL+ DISK KEY to open the BVE-9100 Maintenance menu.
5. Select F2 [INSTALL].
6. Select source drive A.
7. Select the appropriate mixer program from the function bar.
8. Select the destination drive:
 - Drive B for floppy disk
 - Drive G for hard disk
9. Press ENTER to start the installation.

Note: The MXDLG(2).OBJ and MIXER(2).IDC files will automatically be replaced with the updated versions.
10. Reboot the BVE-9100 using the System Disks to load the new version of mixer control program.

CONFIRMATION PROCEDURE

Using the updated System Disk, start up the BVE-9100 and confirm that BZE-9611/01 V5.03 is displayed in INIT MENU 1.

SOFTWARE SET CONTENTS

- This document
- Floppy Disk (BZE-9611/01 MIXER CONTROL PROGRAM V5.03)
- Your licence agreement for the software